

Recessed light fittings in ceilings to intermediate floors in houses

(September 2024) (Third issue – supersedes May 2019)

The Technical Guidance Notes are produced by NHBC as guidance solely for our builder customers as to how to interpret the technical requirements in relation to the warranty cover provided by NHBC under its Buildmark, Buildmark Choice, Buildmark Link, Buildmark Solo, Buildmark Connect or any similar product from time to time. It has not been created or intended for distribution or use outside of that purpose. The information contained in this Technical Guidance Note does not constitute advice and is not to be relied upon by any third party. Nothing in this Technical Guidance Note is intended to, nor should it be taken to, create any legal or contractual relationship. Any third party who chooses to rely upon the information contained in the Technical Guidance Notes shall do so entirely at their own risk and NHBC accepts no duty of care or liability, however caused, in connection with its use or reliance by any third party.

Question

What should be considered when installing recessed light fittings (downlighters) in plasterboard ceilings, to intermediate floors in houses, with regards to fire resistance and isolation from insulation?

Considerations

- Fire resistance of a floor will vary depending on the type of floor deck, joists type e.g. solid, I-joists or metal web joists, and thickness and type of plasterboard used for the ceiling.
- Holes in ceilings will reduce the fire resistance of the ceiling/floor construction.
- Proprietary fire hoods can be used over light fittings to help provide the required fire resistance.
- Certified fire resistant downlighters are available, which achieve fire resistance without further protection.
- To avoid heat build-up and loss of performance, drivers, transformers and lamps should not be covered by insulation.
- Intermediate floors in houses require a modified or full half-hour resistance where the top floor is no higher than 5m from the outside ground level, otherwise they need to achieve 60 minutes.

Answer

Solid timber joists

Non fire-rated downlighters, without further protection, should have fire test evidence for use in a similar solid joist floor build-up, or be fitted with fire hoods. Alternatively, fire resisting downlighters should be used.

Fire-resistant downlighters and fire-resistant hoods are only acceptable if test evidence supports their use in a similar solid joist floor build-up.

I-joists and metal web joists

For engineered floor joists, it is recommended that all recessed downlighters be either fire resistant or fitted with fire hoods.

Fire-resistant downlighters and fire-resistant hoods are only acceptable if test evidence supports their use in a similar engineered joist floor build-up.

General

In all floor types, insulation should be kept back from the light fitting to safely disperse the build up of heat around the driver/ transformer and lamp.



NHBC, NHBC House, Davy Avenue, Knowlhill, Milton Keynes, Bucks MK5 8FP
Tel: 0344 633 1000 Web: nhbc.co.uk

National House-Building Council (NHBC) is authorised by the Prudential Regulation Authority and regulated by the Financial Conduct Authority and the Prudential Regulation Authority for carrying on insurance business and insurance distribution activities.

NHBC is registered in England and Wales under company number 00320784. NHBC's registered address is NHBC House, Davy Avenue, Knowlhill, Milton Keynes, Buckinghamshire, MK5 8FP. Note that only certain parts of our products and services are within the scope of UK financial services regulations. For more information on our products and services, please see our website nhbc.co.uk or your NHBC product documentation.